

1x2(2x2) 200/220µm Multi-Mode Broadband Splitter (Mixer)



Product Features

- Low Insertion Loss
- High Directivity
- Stable and Reliable
- Compact Size

Product Applications

- Optical Communication System
- Fiber Laser
- Optical Sensor
- Access Network

Specifications			Splitting Ratio: 50:50	
Parameter	Unit	1x2 or 2x2		
Grade		Premium	A grade	
Central Wavelength	nm	2000, 1550, 1310, 850		
Bandwidth	nm	±20		
Insertion Loss	Max. dB	4.5	4.7	
Excess Loss	Max. dB	1.5	1.8	
Uniformity	Max. dB	0.5	0.6	
Operating power	Max. W	5		
Operating Temperature	°C	-40 to +85		
Storage Temperature	°C	-50 to +85		
Package Type	mm	S11	Ø4x60: for bare fiber	
		S12	Ø4x70: for 0.9mm loose tube	
		M1	9x16x90: for 0.9mm loose tube or 2mm cable or 3mm cable	

Splitting Ratio & Insertion Loss Conversion Table for 2000, 1550, 1310, 850nm

Splitting Ratio	Maximum Insertion Loss (dB)			
	Premium		A grade	
	Output Port 1	Output Port 2	Output Port 1	Output Port 2
60:40	2.6	4.6	3.0	5.0
70:30	1.9	5.9	2.3	6.3
80:20	1.2	7.8	1.7	8.3
90:10	0.7	11.2	1.2	12
95:5	0.5	15	0.8	16

Ordering Information

M	B	S								
Wavelength	Structure	Splitting Ratio	Grade	Package	Fiber Type	Pigtail	Fiber Length	Connector		
4=1550nm 7=1310nm A=850nm P=2000nm S=Specify	1=1x2 2=2x2	95=95:5 90=90:10 80=80:20 70=70:30 60=60:40 50=50:50	P=Premium A=A grade	A= S11 B= S12 D=M1	V= 200/220µm (NA=0.22)	S=500µm bare fiber M=0.9mm loose tube L=3mm cable R=2mm cable	0=0.5m 1=0.75m 2=1.0m 3=1.5m 4=2.0m S=Specify	O=None		

Note: 1. Central Wavelength can be customized for different applications.
2. All specifications are before connectors and are subject to change without notice.
3. Measured under the stable mode condition with LED source.